

TECHCONNECT OWNERS MANUAL



www.visionaudiovisual.com/techconnect/tc2-lt


TECHCONNECT OWNERS MANUAL

Thanks for choosing the Vision Techconnect! In order to obtain the best performance please be sure to read this owner's manual and use your product only in accordance with the instructions.


CONFORMITY

The product described in this owner manual is in compliance with RoHS (EU directive 2002/95/EC), and WEEE (EU directive 2002/96/EC) standards. Certificates including SGS reports are available on request. This product should be returned to the place of purchase at the end of its useful life for recycling.


WARNINGS




CAUTION
RISK OF ELECTRIC SHOCK
DO NOT OPEN



CAUTION: TO REDUCE THE RISK OF ELECTRIC SHOCK DO NOT REMOVE COVER (OR BACK). NO USER-SERVICEABLE PARTS INSIDE. REFER SERVICING TO QUALIFIED SERVICE PERSONNEL.

 The lightning flash with arrowhead symbol, within an equilateral triangle, is intended to alert the user to the presence of uninsulated "dangerous voltage" within the product's enclosure that may be of sufficient magnitude to constitute a risk of electric shock to persons.

 The exclamation point within an equilateral triangle, is intended to alert the user to the presence of important operating and maintenance (servicing) instructions in the literature accompanying the appliance.


WARNING: TO REDUCE THE RISK OF FIRE OR ELECTRIC SHOCK, DO NOT EXPOSE THIS APPLIANCE TO RAIN OR MOISTURE.

All products are designed and imported into the EU by 'Vision' who is wholly owned by 'Azlan Logistics Ltd.', Registered in England Nr. 04625566 at Lion House, 4 Pioneer Business Park, Clifton Moor, York, YO30 4GH.



WIRING DIAGRAM

VGA & MiniJack Snap-in Module:



	MODULE LABEL	SIGNAL TYPE	CABLE LABEL	CONNECTOR PIN
AUDIO	LE	Left	White	
	G	Ground	Shield	
	RI	Right	Red	
VGA	R	Red	Red	1
	Rs	Red Ground	Red Shield	6
	G	Green	Green	2
	Gs	Green Ground	Green Shield	7
	B	Blue	Blue	3
	Bs	Blue Ground	Blue Shield	8
	H	Horizontal Sync	Brown	13
	Syg	Sync Ground	Black	10+5
	V	Vertical Sync	Yellow	14
	SCL	DDC2B Data Clock	Gray	15
	SDA	DDC2B Bidirectional Data	White	12
	SH	Chassis Ground	Shield	Outer Shield

Note: There is no colour standard for the Horizontal and Vertical Sync cables, so if you use cables not included with the Techconnect, you will need to use a continuity tester to determine which colour on your cable matches which pin on your cable.

3-Phono Module:

	MODULE LABEL	SIGNAL TYPE	CABLE LABEL
3-PHONO	LEFT	Left	White
	LEFT GND	Left Ground	White Shield
	RIGHT	Right	Red
	RIGHT GND	Right Ground	Red Shield
	COMP	Composite Video	Yellow
	COMP GND	Composite Video Ground	Yellow Shield

Note: If using the module for component video substitute white with red, red with green, and yellow with blue.

TROUBLESHOOTING

If you experience a problem, you should narrow down if the problem is with a faulty cable, or a faulty snap-in module. For example, if you cannot get the VGA output of your computer to work:

1. Test a short 2m VGA cable between the projector and computer to make sure it is working.
2. Cut one end of the same cable, strip back wires, and attach to the Techconnect module.

If the image is now displayed, the problem is with your long cable and you should replace it. If the problem persists, you have either wired the wrong cables to the wrong terminals, or the module is faulty.

WARRANTY

This product comes with a 2-year return to base warranty, effective from the date of purchase. This warranty applies only to the original purchaser and is not transferable. For the avoidance of doubt, this will be taken from the information held by the appointed national distributor at the point of sale. If the product is DOA (dead on arrival), you have 21 days from purchase date to notify the national distributor via your AV reseller. The liability of the manufacturer and its appointed service company is limited to the cost of repair and/or replacement of the faulty unit under warranty, except for death or injury (EU85/374/EEC). This warranty protects you against the following:

- Failure of any components, including the power supply.
- Damage when the product is first removed from its packaging if reported within 24 hours of purchase.

If you find you do have a problem with this product, you should contact the AV reseller you purchased this product from. The original purchaser is responsible for shipment of the product to the manufacturer's appointed service centre for repair.

We will endeavour to return repaired units within 5 working days, however this may not always be possible, in which case it will be returned as soon as practicably possible. In line with our WEEE commitments, the manufacturer endeavours to replace the faulty parts of the product rather than replacing the whole unit. This warranty does not protect this product against faults caused by abuse, misuse, incorrect installation, unstable or faulty power input, which might be caused by ignoring the guidelines set out in this manual.

LEGAL DISCLAIMER: Because we are committed to improving our products, the details above may change without prior warning. This User Manual is published without warranty and any improvements or changes to the User Manual necessitated by typographical errors, inaccuracies of current information, or improvements to programs and/or equipment, may be made at any time and without notice. Such changes will be incorporated into new editions of the User Manual.